

Notice

SANYO

CORRECTION
 SERVICE FLASH

PRODUCTION CHANGE
 ADD INFORMATION

FILE NO.

Please add this notice to the Service Manual listed below.

REVISION 1

Category: **COLORTELEVISION**

Date: **May / 15 / 2007**

Model: **DP15647**

Effective from : Chassis No. **P15647-01** ←

Destination: **U.S.A. / CANADA** REF. No. **SM780138**

NOTE: Match the Chassis No. on the unit's back cover with the Chassis No. in the Service Manual. **If the Service Manual Chassis No. does not match the unit's**, additional Service Literature is required. This chassis is similar to Chassis No. P15647-00. Only the **difference** Service Information is given in this manual. For detailed Service Information, refer to the **Original Service Manual** and **Notices** for Chassis No. P15647-00 used in Model DP15647 (SM780138).

Servicing should be performed by only trained and qualified service personnel.

1. IN THE SERVICE ADJUSTMENTS

PAGE 4 ON-SCREEN SERVICE MENU

Item No. 088 OP2 Data should be changed from **00h** to **0Ch** in the table and in **Note 2**.

2. IN THE CHASSIS ELECTRICAL PARTS LIST MAIN PC BOARD AND MISCELLANEOUS

The reason for change.

A : Misprint B : Quality Reliability

C : Standardization

D : Design E : Add as a possible sub


F : Schematic location change

G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 21 Chassis Electrical Parts List	R1263	Old	RGFR000ZTCANL	MT-GLAZE 0.000 JA 1/10W	1	NO	D
		New	RGF1001JTCANL	MT-GLAZE 1K JA 1/10W	1	NO	
	R1266	Old	RGF2201JTCANL	MT-GLAZE 2.2K JA 1/10W	1	NO	D
		New	RGF1001JTCANL	MT-GLAZE 1K JA 1/10W	1	NO	
	R1269	Old	RGFR000ZTCANL	MT-GLAZE 0.000 JA 1/10W	1	NO	D
		New	RGF1001JTCANL	MT-GLAZE1K JA 1/10W	1	NO	
	R1271	Old	RGF2201JTCANL	MT-GLAZE 2.2K JA 1/10W	1	NO	D
		New	RGF1001JTCANL	MT-GLAZE 1K JA 1/10W	1	NO	
Page 22 Chassis Electrical Parts List	R1856	Old	N/A	NOT USED	0	NO	D
		New	RGF4702JTCANL	MT-GLAZE 47K JA 1/10W	1	NO	
	R1857	Old	RGFR000ZTCANL	MT-GLAZE 0.000 JA 1/10W	1	NO	D
		New	NA	NOT USED	0	NO	
	R1858	Old	N/A	NOT USED	0	NO	D
		New	RGF4702JTCANL	MT-GLAZE 47K JA 1/10W	1	NO	
	R1859	Old	RGFR000ZTCANL	MT-GLAZE 0.000 JA 1/10W	1	NO	D
		New	NA	NOT USED	0	NO	
Page 24 Chassis Electrical Parts List	A001	Old	1AA0B10N222F0	ASSY, PWB, MAIN	1	NO	D
		New	1AA0B10N222H0	ASSY, PWB, MAIN	1	NO	
	△EL901	Old	1AV4T40B83400	LCD (CLAA150XP03)	1	NO	D
		New	1AV4T40B84200	LCD (CLAA150XP01Q)	1	NO	
	△U901	Old	1AV4U20C09100	UNIT, INVERTER-POWER	1	NO	D
		New	1AV4U20C11100	UNIT, INVERTER-POWER	1	NO	

3. IN THE SCHEMATIC DIAGRAMS AND PARTS LIST

Add the following parts to the main pc board schematic diagram and parts list.



Schematic Location	Part No.	Description	Schematic Location	Part No.	Description			
CAPACITORS								
C6271	CEXLB1H100VDN	ELECT	10U M	50V	R6271	RGF47R0JTCANL	MT-GLAZE	47 JA 1/10W
	CEXLB1H100WAN	ELECT	10U M	50V	R6272	RGF47R0JTCANL	MT-GLAZE	47 JA 1/10W
C6272	CK1H104ZLZFNG	CERAMIC	0.1U Z	50V	R6273	RGF1002JTCANL	MT-GLAZE	10K JA 1/10W
C6273	CK1H104ZLZFNG	CERAMIC	0.1U Z	50V	R6276	RGF6800JTCANL	MT-GLAZE	680 JA 1/10W
C6274	CEXLB1H100VDN	ELECT	10U M	50V	R6277	RGF47R0JTCANL	MT-GLAZE	47 JA 1/10W
	CEXLB1H100WAN	ELECT	10U M	50V	R6278	RGF47R0JTCANL	MT-GLAZE	47 JA 1/10W
C6276	CK1H104ZLZFNG	CERAMIC	0.1U Z	50V	R6281	RGF1002JTCANL	MT-GLAZE	10K JA 1/10W
C6277	CEXLB1H100VDN	ELECT	10U M	50V	R6282	RGF6800JTCANL	MT-GLAZE	680 JA 1/10W
	CEXLB1H100WAN	ELECT	10U M	50V				
C6278	CK1A105ZLZFNG	CERAMIC	1U Z	10V				
C6279	CK1H472KLZBNG	CERAMIC	4700P K	50V				
C6281	CK1H104ZLZFNG	CERAMIC	0.1U Z	50V				
C6282	CEXLB1H100VDN	ELECT	10U M	50V				
	CEXLB1H100WAN	ELECT	10U M	50V				
C6283	CK1A105ZLZFNG	CERAMIC	1U Z	10V				
C6284	CK1H472KLZBNG	CERAMIC	4700P K	50V				
INTEGRATED CIRCUITS								
IC6270	QXXAVC859--P	IC WM8738GED/RV						
COILS								
L6270	RGFR000ZTAANL	MT-GLAZE	0.000 ZA	1/10W				
L6271	RGFR000ZTAANL	MT-GLAZE	0.000 ZA	1/10W				

For parts or service contact

**Sanyo Manfacturing Corporation
P.O. Box 2000
3333 Sanyo Road
Forrest City, Arkansas 72335-2000**